B Serisi Ø 22 mm Adaptörlü Kumanda Butonu Tipleri
Series Ø 22 mm Push Buttons With Adapter

Sinyaller / *Pilot Lights*

Ürün Kodu	Işık	Nominal Gerilim	Renk
Code	*Illimunation*	*Nominal Voltage*	*Colour*
B030X*	Ba9S Duylu		B K M S Y H
B050XB	Led	12 - 30V AC/DC	B
B060XK	Led	12 - 30V AC/DC	K
B070XM	Led	12 - 30V AC/DC	M
B080XS	Led	12 - 30V AC/DC	S
B090XY	Led	12 - 30V AC/DC	Y
B0B0XB	Led	100 - 230V AC	B
B0K0XK	Led	100 - 230V AC	K
B0M0XM	Led	100 - 230V AC	M
B0S0XS	Led	100 - 230V AC	S
B0Y0XY	Led	100 - 230V AC	Y



B080XS



B050XB

Kontak Blok Tipler / *Contac Block Types*

Ürün Kodu	Kontak Blok Tipi		Işık	Nominal Akım	Nominal Gerilim	Renk
Code	*Contact Block Type*		*Illimunation*	*Nominal Current*	*Nominal Voltage*	*Colour*
	Normal Açık *Normally Open*	Normal Kapalı *Normally Closed*				
B1	1		-	4A	250V	-
B2		1	-	4A	250V	-
B3			Ba9S Duylu	-	-	-
B5			Led	5-20mA	12-30V AC/DC	B
B6			Led	5-20mA	12-30V AC/DC	K
B7			Led	5-20mA	12-30V AC/DC	M
B8			Led	5-20mA	12-30V AC/DC	S
B9			Led	5-20mA	12-30V AC/DC	Y
BB			Led	5-15mA	100-230V AC	B
BK			Led	5-15mA	100-230V AC	K
BM			Led	5-15mA	100-230V AC	M
BS			Led	5-15mA	100-230V AC	S
BY			Led	5-15mA	100-230V AC	Y
BB4			Led	4-5mA	110V AC/DC	B
BK4			Led	4-5mA	110V AC/DC	K
BM4			Led	4-5mA	110V AC/DC	M
BS4			Led	4-5mA	110V AC/DC	S
BY4			Led	4-5mA	110V AC/DC	Y

• Max. 2W'lık Ba9S duylu Neon Ampul takılabilir.
• Assembly possibility only for Neon Lamp with max. 2W socket.

• • Maksimum 3 adet kontak blok arka arkaya eklenebilir.
• • Max. 3 contact blocks can be added subsequently.



B1



B2



B3



B9